

8155W  
**1/2 HP AC BELT DRIVE WI-FI®  
GARAGE DOOR OPENER**

Dependable performance.



**KEY FEATURES**

**QUIET OPERATION**  
Belt Drive

**WI-FI**  
Built In



myQ integrates with leading smart home platforms. Visit [myQ.com](http://myQ.com) to learn more.

**RELIABLE**

**1/2 HP AC MOTOR** IS PURPOSEFULLY DESIGNED AND BUILT TO LAST.

**BELT DRIVE SYSTEM** FOR QUIET, MAINTENANCE-FREE PERFORMANCE.

**WARRANTY** 4-YEAR MOTOR, 1-YEAR PARTS.

**SMART**

**BUILT-IN WI-FI** FOR THE EASIEST WAY TO CONNECT THE GARAGE.

**myQ MOBILE APP** LETS USERS RECEIVE ALERTS AND CONTROL THE OPENER FROM ANYWHERE.

**SECURE**

**SECURITY+ 2.0®** SENDS A NEW CODE WITH EVERY REMOTE CLICK.

**POSILOCK®** ELECTRONICALLY PROTECTS AGAINST FORCED OPENINGS.

**ALERT-2-CLOSE** SIGNALS WHEN A DOOR IS BEING CLOSED BY myQ.

**THE PROTECTOR SYSTEM®** INVISIBLE LIGHT BEAM AUTO-REVERSES THE DOOR IF THERE IS AN OBSTRUCTION.

**INCLUDED ACCESSORIES:**

**MULTI-FUNCTION CONTROL PANEL®**  
Includes lockout controls and accessory programmability.



**882LMW**

**1-BUTTON REMOTE CONTROL**  
Operates a single opener.



**891LM**

**POWERFUL ADD-ONS:**

**myQ HOME BRIDGE**  
Adds Apple® HomeKit™ compatibility and Siri® voice control to Wi-Fi-enabled openers. Installs easily in the garage within Wi-Fi range.\*\*



**819LMB**

**MINI UNIVERSAL REMOTE CONTROL**  
Compact and portable to provide quick, easy garage access.



**374UT**

Smartphone not included.

**PRODUCT GUIDE 8155W**  
**1/2 HP AC BELT DRIVE WI-FI**  
**GARAGE DOOR OPENER**

**LiftMaster®**

# MASTERFUL ENGINEERING.

1/2 HP AC BELT DRIVE WI-FI®  
GARAGE DOOR OPENER

## MOTOR

- 1/2 Horsepower AC
- 1,625 RPM
- Automatic Thermal Protection
- Permanent Lubrication

## POWER

- 120V AC
- 60 Hz Voltage
- 6A Current Rating
- UL® Listed
- 4' Power Cord (3-Prong)

## MECHANICS

- Steel Chassis, T-Rail and Trolley
- Full Reinforced Belt Drive Mechanism (16:1 Gear Reduction and Adjustable Door Arm)
- Auto-Force Adjustment for Changing Weather and Environmental Conditions
- Electronic Limits for Easy Setup
- AC Wi-Fi Logic Board with Built-In Surge Suppressor (for Replacement Logic Boards, Order Part 050ACTWF)

5.75"



15"

16"

## DIMENSIONS

| Rail Options     | 7'   | 8'   | 10'   |
|------------------|------|------|-------|
| Installed Length | 124" | 136" | 160"  |
| Max. Opening     | 7'6" | 8'6" | 10'6" |

Headroom Clearance Required: 2"

7"

Per second for door to move upward

## SPEED

7"

Per second for door to move downward

# STANDARD SPECS.

## SECURITY

### SECURITY+ 2.0®

#### RADIO CONTROLS

3-Button Remote Control (893LM)

Operating Range: ~200'

Operating Temperature: -30°F to 150°F

Frequency:

- Remote Control Code Format: Security+2.0
- Garage Door Opener Code Format: Security+2.0
- Security+ 2.0 Anti-Burglary Coding

### SECURITY+ 2.0

#### ENCRYPTED CONTROLS

Multi-Function Control Panel® (882LMW)

- Program Remote Controls
- Maintenance Alert System
- Easy Wi-Fi Setup

## SMART

### myQ® RADIO

902-928 MHz  
50-Channel FHSS  
(Frequency Hopping Spread Spectrum)

- Provides 2-way communication from garage door opener and myQ Accessories.
- Enables monitoring and control of garage door openers via smartphone or tablet.

### HOMELINK® COMPATIBLE

#### (VERSION 4.0 OR HIGHER\*)

\*May require an external adapter depending on the model and year of your vehicle. Visit HomeLink.com for additional information.

## ELECTRICAL

### LIGHTING



- Max. 1 100-Watt Lightbulb
- Enhanced CFL (Compact Fluorescent) Compatible, Max. 26 Watts

# SHIPPING.

SHIPPING WEIGHT (in lbs.)

20  
HEAD

17  
RAIL (7')

## CARTONS (2)

CARTON 1: 20" x 12" x 10"

- Multi-Function Control Panel (882LMW)
- 3-Button Remote Control (893LM)
- Garage Door Opener Head (8155W)
- The Protector System® Safety Reversing Sensors

CARTON 2: 10'4" x 5" x 5" (for 7' Rail)

- Assembled Solid-Steel Chain T-Rail

# CONVENIENCE AND SAFETY.



- Alert-2-Close with Unattended Close Operation†
- Emergency/Quick Release
- Automatic Trolley Reconnect
- Ventilation/Pet Opening
- Down Safety Reverse
- Up Safety Stop
- Maintenance Alert System
- Garage Door Opener Capacity of up to 12 Remote Controls, 1 Keyless Entry System and 16 myQ Devices

\*WARNING: to reduce the risk of injury to persons—ONLY enable Timer-to-Close and MyQ remote operation features when opener is installed on a sectional door.